

PREZONE444 MKII

8-channel mixer with 4 independent output zones
- Each input can be routed to the zone of your choice
- Compatible with WP1 wall controller
- Compatible with MIC-DESK4 4-zone console

SKU: H11767
Categories: Audio mixers
Tags: New

FEATURES

– 4 balanced Mic/Line inputs on XLR and Jack 6.35 (TRS)
– 4 stereo inputs on RCA or Mono on 6.35 jack
– 4 balanced link out per zone on Phoenix plug
– Priority microphone on input 1
– Phantom power supply for inputs 1 to 4
– Gain and tone control (3 bands) on channels 1 to 4
– Gain adjustment on all inputs
– Tone control (2 bands) per zone
– RJ45 connector for WP-1 wall controller (remote input) and MIC-DESK desk (remote mic) on each zone
– Mute contact possible on each output
– Zone assignment 1 to 4 on each input channel
– Signal and Peak display on each input channel
– Output level display per zone via 5 LED meter
– Headphone output with volume control (zones and PFL)
– Front monitor speaker
– Access to settings dedicated to the installer (via screwdriver)
– Power supply: AC 100~240V / 50~60Hz or +24V DC
– Power consumption: 17 Watts
– DC24 V emergency power supply with Link Out
– Frequency response: 20 Hz – 20 kHz (- 1dB)
– T.H.D (1 kHz nominal power) : < 0,1% - Equalizer : - High : +/-15 dB @ 12kHz - Mid: +/-15 dB @ 2.5 kHz - Low +/- 15 dB @ 80 Hz -

Dimensions: 320 x 88 x 482 mm - 19 inch rackable - Height: 2 units - Weight: 4.7 kg

USER MANUALS

Guide de l'utilisateur / User guide

⬇ Guide de l'utilisateur / User guide

Gebruikershandleiding

⬇ Gebruikershandleiding

Benutzerhandbuch

⬇ Benutzerhandbuch

Guía del usuario

⬇ Guía del usuario

CE CERTIFICATE

Declaration of conformity

⬇ Français / English

