



BM-A1000

Magnetic loop amplifier for areas up to 1000 m², with loop impedance between 0.5 and 3 ohms



SKU: H10797

Categories: [Magnetic loop](#)

Tags: [Magnetic loop](#)

FEATURES

- Class D amplifier for approx. 1000^{m2}
- 3 inputs: 2 line or microphone inputs
(connector: 1 Phoenix and Combo), 1 priority 100V input
- Monitoring and fault detection of power supply, amplifier and loop with NO-NC relay.
 - Integrated phase-shift module (90° or 0° output)
 - Automatic gain control
 - Metal loss correction adjustment
 - Power supply: 230 V 50/60 Hz
 - Dimensions: 483 x 43 x 215 mm
 - Weight: 2.47 kg

USER MANUALS

FR



EN



NL

