



COMBO120EVO

100 V, 120 W amplifier-mixer with integrated media player:
USB, FM tuner, Bluetooth and DAB+.



SKU: H11657

Categories: [100 V amplifiers](#), [Audio mixers](#)

Tags: [New](#)

FEATURES

Power:

100V : 120 Watts

70V : 120 Watts

4Ω : 120 Watts

Input sensitivity:

CH 1: -52 dBV

CH 2: -10 dBV

CH 3: -10 dBV

AUX: -10 dBV

Frequency response:

80 Hz – 16 kHz (± 3 dB)

Signal-to-noise ratio:

CH 1 : ≥ 65 dB

CH 2 : ≥ 65 dB

CH 3 : ≥ 65 dB

AUX : ≥ 75 dB

T.H.D+N:

< 1% @ 1/8 RMS

Equalization:

BASS: ± 10 dB (at 100 Hz)
TREBLE: ± 10 dB (at 1 kHz)

Output voltages:

4 Ω / 70V / 100V

Power circuit:

Class D switching power supply

Power supply:

AC 220-240V, 50/60 Hz
DC 24V

Protections:

Short circuit / Open circuit / Thermal / Limiter / Ultrasound and radio frequency

Connections:

4 MIC / LINE combo connectors
1 AUX input on RCA
1 TEST/ALARM input
1 balanced LINE OUT pre or post fader output
1 coaxial connector for antenna

Settings:

Input level
Player level
AUX input level
Bass and treble equalization
CH 1 input priority
Overall level

Cooling:

By thermoregulated ventilation

Dimensions:

483 x 281 x 44 mm

Net weight:

4.9 kg

USER MANUALS

Notice FR/EN



