



COMBO240EVO

240 W, 100 V amplifier-mixer with integrated media player:
USB, FM tuner, Bluetooth and DAB+.



SKU: H11658

Categories: [Audio mixers](#)

FEATURES

Power:

100V : 240 Watts

70V : 240 Watts

4Ω : 240 Watts

Input sensitivity:

CH 1: -52 dBV

CH 2: -10 dBV

CH 3: -10 dBV

AUX: -10 dBV

Frequency response:

80 Hz – 16 kHz (± 3 dB)

Signal-to-noise ratio:

CH 1: ≥ 65 dB

CH 2: ≥ 65 dB

CH 3: ≥ 65 dB

AUX: ≥ 75 dB

T.H.D+N :

< 1% @ 1/8 RMS **Equalization:**

BASS: ± 10 dB (at 100 Hz)

TREBLE: ± 10 dB (at 1 kHz)

Output voltages:

4 Ω / 70V / 100V

Power circuit:

Class D switching power supply

Power supply:

AC 220-240V, 50/60 Hz

DC 24V

Protections:

Short circuit / Open circuit / Thermal / Limiter / Ultrasound and radio frequency

Connections:

4 Combo MIC / LINE connectors

1 AUX input on RCA

1 TEST/ALARM input

1 balanced LINE OUT pre or post fader

1 coaxial connector for antenna

Multimedia player:

Supported audio formats: MP3, WAV, WMA

Maximum media capacity: 128 GB (flash memory)

Format: FAT32

Settings:

Input level

Player level

AUX input level

Bass and treble equalization

CH 1 input priority

Overall level

Cooling:

By thermoregulated ventilation

Dimensions:

483 x 281 x 44 mm

Net weight:

6.6 kg

USER MANUALS

Notice FR/EN



Notice DE



Notice NL



Notice ES



DOWNLOAD



– Update to display DAB+ station names

[Download update](#)

CE CERTIFICATE

FR / EN



