

COMBO240EVO

240 W, 100 V amplifier-mixer with integrated media player:
USB, FM tuner, Bluetooth and DAB+.

SKU: H11658
Categories: Audio mixers

FEATURES

Power:
100V : 240 Watts
70V : 240 Watts
4Ω : 240 Watts

Input sensitivity:
MIC: -52 dBV
LINE: -10 dBV
AUX: -10 dBV
Phantom power: -52 dBV / 18 V balanced

Frequency response:
80 Hz – 16 kHz (± 3 dB)

Signal-to-noise ratio:
MIC: ≥ 65 dB
LINE: ≥ 75 dB
AUX: ≥ 75 dB

T.H.D+N :
≤ 1% @ 1/8 RMS

Equalization:
BASS: ± 10 dB (at 100 Hz)

TREBLE: ± 10 dB (at 1 kHz)

Output voltages:
4Ω / 70V / 100V

Power circuit:
Class D switching power supply

Power supply:
AC 100-240V, 50/60 Hz
DC 24V

Protections:
Short circuit / Open circuit / Thermal / Limiter / Ultrasound and radio frequency

Connections:
4 Combo MIC / LINE connectors
1 AUX input on RCA
1 TEST/ALARM input
1 balanced LINE OUT pre or post fader
1 coaxial connector for antenna

Multimedia player:
Supported audio formats: MP3, WAV, WMA
Maximum media capacity: 128 GB (flash memory)
Format: FAT32

Settings:
Input level
Player level
AUX input level
Bass and treble equalization
CH 1 input priority
Overall level

Cooling:
By thermoregulated ventilation

Dimensions:
483 x 281 x 44 mm

Net weight:
5.6 kg

USER MANUALS

Guide de l'utilisateur / User guide

⬇ Guide de l'utilisateur / User guide

Gebruikershandleiding

⬇ Gebruikershandleiding

Benutzerhandbuch

⬇ Benutzerhandbuch

Guía del usuario

⬇ Guía del usuario

DOWNLOAD



– Update to display DAB+ station names

Download update

CE CERTIFICATE

Declaration of conformity

⬇ Français / English


CH 1
CH 2
CH 3
CH 4
AUX
ANT