

COMBO60

Mixer/Amplifier/Multimedia player combo

- Compact all-in-one system
- Built-in USB drive and tuner
- Microphone input and two line inputs
- Compatible with paging and music on hold
- Safety priority exit
- 3-band equalizer

SKU: H9749
Categories: 100 V amplifiers, Amplifiers, Audio mixers, Multimedia players

FEATURES

Compact 60W all-in-one system
– Mixer 3 inputs:
– 2 mic channels – Aux1/MP3/TUNER
– Bass, midrange and treble control
– mp3 player and tuner control
– Output level meter
– 6.35 jack input for microphone
– AUX and CD input on RCA
– Music on hold input on Phoenix plug
– Telepaging input on Phoenix plug – Connections for FM and AM antennas
– Outputs 100V / 16 / 8 / 4 Ohms on terminal block
– Receiver Tuner : AM / FM
– Autoscan, Manual search
– FM frequencies: 87.5 MHz – 108 MHz
– AM frequencies: 522 kHz – 1620 kHz
– USB drive: mp3 files

– Functions: play, search, track programming
– Power supply: 220 V 50-60 Hz
– Power consumption: 175 W
– Dimensions: 90 x 270 x 260 mm
– Net weight: 5 kg

CE CERTIFICATE

Declaration of conformity

⬇ Français / English

