



COMBO60

Mixer/Amplifier/Multimedia player combo

- Compact all-in-one system
- Built-in USB drive and tuner
- Microphone input and two line inputs
- Compatible with paging and music on hold
 - Safety priority exit
 - 3-band equalizer



SKU: H9749

Categories: [Amplifiers](#), [Audio mixers](#), [Multimedia players](#)

FEATURES

- Compact 60W all-in-one system
 - Mixer 3 inputs:
 - 2 mic channels – Aux1/MP3/TUNER
 - Bass, midrange and treble control
 - mp3 player and tuner control
 - Output level meter
 - 6.35 jack input for microphone
 - AUX and CD input on RCA
 - Music on hold input on Phoenix plug
 - Telepaging input on Phoenix plug – Connections for FM and AM antennas
 - Outputs 100V / 16 / 8 / 4 Ohms on terminal block
 - Receiver Tuner : AM / FM
 - Autoscan, Manual search
 - FM frequencies: 87.5 MHz – 108 MHz
 - AM frequencies: 522 kHz – 1620 kHz
 - USB drive: mp3 files
 - Functions: play, search, track programming

- Power supply: 220 V 50-60 Hz
- Power consumption: 175 W
- Dimensions: 90 x 270 x 260 mm
 - Net weight: 5 kg

