



COMBO60EVO

60 W, 100 V amplifier-mixer with integrated media player: USB, FM tuner, Bluetooth and DAB+.



SKU: H11656

Categories: [Audio mixers](#)

FEATURES

Power:

100V : 60 Watts

70V : 60 Watts

4Ω : 60 Watts

Input sensitivity:

MIC: -52 dBV

LINE: -10 dBV

AUX: -10 dBV

Phantom power: -52 dBV / 12 V balanced

Frequency response:

80 Hz – 16 kHz (± 3 dB)

Signal-to-noise ratio:

MIC: ≥ 65 dB

CH 1: ≥ 65 dB

CH 2: ≥ 65 dB

AUX: ≥ 75 dB

T.H.D+N :

< 1% @ 1/8 RMS **Equalization:**

BASS: ± 10 dB (at 100 Hz)

TREBLE: ± 10 dB (at 1 kHz)

Output voltages:

4 Ω / 70V / 100V

Power circuit:

Class D switching power supply

Power supply:

AC 220-240V, 50/60 Hz

DC 24V

Protections:

Short circuit / Open circuit / Thermal / Limiter / Ultrasound and radio frequency

Connections:

2 Combo connectors

1 AUX input on RCA

1 coaxial connector for antenna

Multimedia player:

Supported audio formats: MP3, WAV, WMA

Maximum media capacity: 128 GB (flash memory)

Format: FAT32

Settings:

Input level

Player level

AUX input level

Bass and treble equalization

Overall level

Cooling:

By convection

Dimensions:

320 x 220 x 73 mm

Net weight:

2.73 kg

USER MANUALS

Notice FR/EN



Notice DE



Notice NL



Notice ES



DOWNLOAD



– Update to display DAB+ station names

[Download update](#)

CE CERTIFICATE

EN



