



## PREZONE444 MKII

- 8-channel mixer with 4 independent output zones
- Each input can be routed to the zone of your choice
  - Compatible with WP1 wall controller
  - Compatible with MIC-DESK4 4-zone console



SKU: H11767

Categories: [Audio mixers](#)

Tags: [New](#)

## FEATURES

- 4 balanced Mic/Line inputs on XLR and Jack 6.35 (TRS)
  - 4 stereo inputs on RCA or Mono on 6.35 jack
  - 4 balanced link out per zone on Phoenix plug
    - Priority microphone on input 1
    - Phantom power supply for inputs 1 to 4
  - Gain and tone control (3 bands) on channels 1 to 4
    - Gain adjustment on all inputs
    - Tone control (2 bands) per zone
- RJ45 connector for WP-1 wall controller (remote input) and MIC-DESK desk (remote mic) on each zone
  - Mute contact possible on each output
  - Zone assignment 1 to 4 on each input channel
  - Signal and Peak display on each input channel
  - Output level display per zone via 5 LED meter
- Headphone output with volume control (zones and PFL)
  - Front monitor speaker
- Access to settings dedicated to the installer (via screwdriver)
  - Power supply: AC 100~240V / 50~60Hz or +24V DC
    - Power consumption: 17 Watts
  - DC24 V emergency power supply with Link Out
  - Frequency response: 20 Hz – 20 kHz (- 1dB)
- T.H.D (1 kHz nominal power) : < 0,1% - Equalizer : - High : +/-15 dB @ 12kHz - Mid: +/-15 dB @ 2.5 kHz - Low +/- 15 dB @ 80 Hz -

Dimensions: 320 x 88 x 482 mm - 19 inch rackable - Height: 2 units - Weight: 4.7 kg

### USER MANUALS

Instructions EN



EN notice



DE leaflet



Notice NL



ES leaflet



