



PREZONE444

- 8-channel mixer with 4 independent output zones
- Each input can be routed to the zone of your choice
 - Compatible with WP1 wall controller
 - Compatible with MIC-DESK4 4-zone console



SKU: H10507

Categories: [Audio mixers](#)

FEATURES

- 4 balanced Mic/Line inputs on XLR and Jack 6.35 (TRS)
 - 4 stereo inputs on RCA or Mono on 6.35 jack
 - 4 balanced link out per zone on Phoenix plug
 - Priority microphone on input 1
 - Phantom power supply for inputs 1 to 4
 - Gain and tone control (3 bands) on channels 1 to 4
 - Gain adjustment on all inputs
 - Tone control (2 bands) per zone
- RJ45 connector for WP-1 wall controller (remote input) and MIC-DESK desk (remote mic) on each zone
 - Mute contact possible on each output
 - Zone assignment 1 to 4 on each input channel
 - Signal and Peak display on each input channel
 - Output level display per zone via 5 LED meter
- Headphone output with volume control (zones and PFL)
 - Front monitor speaker
- Access to settings dedicated to the installer (via screwdriver)
 - Power supply: 230 V 50/60 Hz and DC 24V
 - Power consumption : 30 Watts
 - DC24 V emergency power supply with Link Out
 - Frequency response: 20 Hz – 20 kHz (+/- 3dB)
- T.H.D (1 kHz nominal power) : < 0,1% - Equalizer : - High : +/-15 dB @ 12kHz - Mid: +/-15 dB @ 2.5 kHz - Low +/- 15 dB @ 80 Hz -

Dimensions: 320 x 088 x 482 mm - 19 inch rackable - Height: 2 units - Weight : 5 kg

USER MANUALS

Notice FR



Notice EN

